



SECOND FLOOR PLAN - ELECTRICAL DEMOLITION
SCALE: 1/8" = 1'-0"

- NOTES :**
1. THESE DRAWINGS SHALL NOT BE SCALED.
 2. THE CONTRACTOR SHALL VISIT THE SITE AND SATISFY HIMSELF ALL DIMENSIONS, DATUM, AND DETAILED INFORMATION SHOWN ARE CORRECT.
 3. THE CONTRACTOR IS TO REPORT ANY DISCREPANCIES PRIOR TO COMMENCEMENT OF WORK.
 4. THE CONTRACTOR IS TO REVIEW AND COORDINATE ALL ARCHITECTURAL, MECHANICAL, ELECTRICAL AND STRUCTURAL DRAWINGS FOR ADDITIONAL OPENINGS THROUGH FLOORS, WALLS, AND CEILINGS FOR DUCT, PIPE & ELECTRICAL RISERS AND ALL OPENINGS NOT SHOWN ON DRAWINGS.
 5. ALL OPENINGS THROUGH FIRE ASSEMBLIES ARE TO BE FIRE STOPPED AND SEALED WITH UL-C APPROVED FIRE STOPPING TO MAINTAIN THE INTEGRITY OF THE FIRE SEPARATION, AND PROVIDE A SMOKE-TIGHT BARRIER.
 6. ALL PRODUCTS AND MATERIALS TO BE USED AND INSTALLED SHALL CONFORM WITH MANUFACTURERS SPECIFICATIONS & APPLICABLE CODES.
 7. THE CONTRACTOR SHALL BE RESPONSIBLE TO PATCH AND MAKE GOOD ALL EXISTING CONSTRUCTION AFFECTED BY THE REMOVAL OF ALL ITEMS FORMING THE PART OF THE RENOVATION WORK.
 8. WHERE NEW FLOORING AND BASE IS TO BE INSTALLED IN EXISTING AREAS (REFER TO FLOOR PLAN AND ROOM SCHEDULE) THE EXISTING FLOORING SURFACE AND BASE MUST BE REMOVED, UNLESS OTHERWISE NOTED. ALL FLOOR SURFACES SHALL BE PREPARED IN ACCORDANCE TO MANUFACTURERS RECOMMENDATIONS FOR INSTALLATION OF NEW FLOOR.
 9. WHERE PAINTING OF EXISTING WALLS IS INDICATED ON THE ROOM SCHEDULE, THESE WALLS MUST BE CLEANED OF ANY EXISTING WALL COVERING, PATCHED & PREPARED TO ACCEPT NEW MATERIAL, UNLESS OTHERWISE NOTED.
 10. ALL NEW LIGHTING FIXTURES & NEW RECEPTACLES TO BE CONNECTED TO APPROPRIATE PANELS. EXCEPT FOR EMERGENCY LIGHT REMOTE HEADS TO BE CONNECTED TO EMERGENCY LIGHT BATTERY PACK(S).
 11. CONTRACTOR MAY REUSE EXISTING BREAKERS & WIRING PROVIDED SAME IS IN GOOD CONDITION & MEETS ALL APPLICABLE CODES.
 12. GENERAL DUTY RECEPTACLES SHALL BE CSA APPROVED, BLACK C/W, STAINLESS STEEL TRIM PLATES MOUNTED AT 14" FROM FLOOR, EXCEPT FOR GFCI RECEPTACLES.
 13. DIMMERS SHALL BE CSA APPROVED COMMERCIAL SLIDE TYPE TO SUIT CIRCUIT LOAD.
 14. SUPPLY & INSTALL LAMACOID NAME PLATES ON ALL PANEL BOARDS, SWITCHES & RECEPTACLES. PANEL SCHEDULE SHALL BE TYPED & ADHERED TO INSIDE OF ASSOCIATED PANEL DOOR.
 15. ALL ABANDONED ELECTRICAL FIXTURES, COMPONENTS & RECEPTACLE WIRINGS SHALL BE REMOVED BACK TO SOURCE.

ORIGINAL SEALED BY:
D.A. Paley P. Eng.
Date: 2004/10/15

ELECTRICAL SYMBOLS

SYMBOL	DESCRIPTION	SYMBOL	DESCRIPTION
(A)	FLUORESCENT LIGHT 2X4 (EXISTING)	(S)	SMOKE DETECTOR (IONIZATION)
(A1)	FLUORESCENT LIGHT 2X4 (EXISTING NIGHTLIGHT)	(H)	HEAT DETECTOR (Fixed T.)
(B)	FLUORESCENT LIGHT 2X4 REUSE &/OR NEW	(F)	FIRE ALARM BELL
(C)	FLUORESCENT LIGHT 1X4 (EXISTING)	(P)	FIRE ALARM PULL STATION
(C1)	FLUORESCENT LIGHT 1X4 (EXISTING NIGHTLIGHT)	(D)	DATA - WALL
(L)	CEILING LIGHT (NEW)	(T)	TELEPHONE - WALL (EXIST)
(LE)	CEILING EMERG. LIGHT (EXISTING)	(T1)	TELEPHONE - WALL (NEW)
(L1)	CEILING EMERG. LIGHT (NEW)	(T2)	TELEPHONE - WALL (REMOVE)
(EXIT-1)	EXIT LIGHT (EXISTING)	(F1)	FLOOR TELEPHONE
(EXIT-2)	EXIT LIGHT (NEW)	(LH)	EMG LITE HEAD
(D)	DUPLEX RECEPTACLE	(B)	EMG LITE BATTERY
(D1)	FLOOR DUPLEX RECEPT.	(S1)	SINGLE POLE SWITCH
(P)	POWERPOLE	(S3)	3 WAY SWITCH
(DR)	DRYER RECEPT.	(S3)	3-GANG SWITCHES
(EH)	ELECTRIC BASEBOARD HEATER (EXISTING)	(S3M)	DIMMER SWITCH
		(S2)	2-GANG SWITCHES
		(S2H)	SWITCH-EXHAUST FAN
		(E)	EXHAUST FAN
		(T)	THERMOSTAT
		(W)	WALL INTD SPEAKER
		(CS)	CARBON MONOXIDE SENSOR (EXISTING)

ELECTRICAL DEMOLITION NOTES:

REFER TO DRAWING E-6 AND NOTES.
..... INDICATES DEMOLITION. INCLUDES ELECTRICAL SYMBOLS.

- 1 REMOVE (SHOWN IN DASH) RECEPTACLES, CONNECTORS, & ASSOCIATED WIRING BACK TO SOURCE. TYPICAL.
- 2 REMOVE (SHOWN IN DASH) COMPLETE DATA BOX, CONNECTOR, & ASSOCIATED CABLING BACK TO SOURCE. TYPICAL.
- 3 REMOVE DATA CONNECTOR & CABLING BACK TO SOURCE. DO NOT REMOVE DATA BOX IN WALL. TYPICAL.
- 4 REMOVE TELEPHONE OUTLET & CABLING BACK TO SOURCE. PATCH WALL TO MATCH EXISTING, EXCEPT WHERE WALL IS TO BE DEMOLISHED. TYPICAL.
- 5 REMOVE & DISPOSE FIRE HORN, PANELS, CONTROLS, CONNECTED TO FM-200 FIRE SUPPRESSION SYSTEM. CONTACT CITY OF WINNIPEG CENTRAL CONTROL AT 986-2351 PRIOR TO REMOVAL.
- 6 REMOVE & DISPOSE DRYER RECEPTACLE & WIRING BACK TO SOURCE. PATCH WALL TO MATCH EXISTING.
- 7 REMOVE ELECTRICAL PANELS, CONDUIT & WIRING UNDER COUNTER BACK TO SOURCE.

DRAWING LIST (ELECTRICAL, DATA & PHONE)

E-1	ELECTRICAL, DATA & PHONE DEMOLITION
E-2	ELECTRICAL, DATA & PHONE RENOVATION
E-3	ELECTRICAL LIGHTING DEMOLITION
E-4	ELECTRICAL LIGHTING RENOVATION
E-5	SECURITY ALARM & CARD ACCESS CONTROL SYSTEM
E-6	ELECTRICAL & CATEGORY 6 CABLING SPECIFICATIONS

NO.	REVISION/DESCRIPTION	BY	DATE
SEALS			

DRAWN BY DTA **CHECKED BY** USER **APPROVED** USER

DATE 2004.10.13

CITY OF WINNIPEG
PLANNING, PROPERTY & DEVELOPMENT DEPARTMENT
CIVIC ACCOMMODATIONS DIVISION
300 - 65 GARRY ST. 3R3 4K4

PROJECT
Fire Paramedic Services
Executive Office Renovation
185 KING STREET - MANDARIN BLDG. - SECOND FLOOR

SHEET TITLE
ELECTRICAL, DATA & PHONE DEMOLITION

SCALE AS SHOWN	PROJECT NO. 2004-060	SHEET NO. E-1
--------------------------	--------------------------------	-------------------------

DRAWING SHEET SIZE: A1 (594mm x 841mm) PLOT 1:1