

Part 1 General

1.1 REFERENCES

- .1 Canadian Standards Association (CSA International)
 - .1 CSA C22.1-06, Canadian Electrical Code, Part 1 (20th Edition), Safety Standard for Electrical Installations.
 - .2 CSA C22.2.
 - .3 CAN/CSA-C22.3 No. 1, Overhead Systems.
 - .4 CAN3-C235-83(R2000), Preferred Voltage Levels for AC Systems, 0 to 50,000 V.
- .2 Electrical and Electronic Manufacturer's Association of Canada (EEMAC)
 - .1 EEMAC 2Y-1-1958, Light Gray Colour for Indoor Switch Gear.
- .3 Institute of Electrical and Electronics (IEEE)/National Electrical Safety Code Product Line (NESC)
 - .1 IEEE SP1122-2000, The Authoritative Dictionary of IEEE Standards Terms, 7th Edition.

1.2 CONTRACTOR REQUIREMENTS

- .1 Comply with all Department of Labor, Workplace and Health requirements at all times.
- .2 All Contractors shall have a valid Contractors license to operate in the City of Winnipeg.
- .3 All Electrical Contractor employees on Site shall have valid Trade Licenses.
- .4 Electrical Contractor shall maintain the appropriate ratio of Journeymen Electricians & Apprentices required by Provincial Codes.
- .5 Obtain all necessary permits & pay all fees and arrange for inspection with City of Winnipeg.
- .6 Obtain a certificate of final inspection and approval from inspection department having jurisdiction on completion of work.

1.3 DEFINITIONS

- .1 Electrical and electronic terms: unless otherwise specified or indicated, terms used in these specifications, and on drawings, are those defined by IEEE SP1122.

1.4 DESIGN REQUIREMENTS

- .1 Operating voltages: to CAN3-C235.
- .2 Motors, electric heating, control and distribution devices and equipment to operate satisfactorily at 60 Hz within normal operating limits established by above standard.

- .1 Equipment to operate in extreme operating conditions established in above standard without damage to equipment.
- .3 Language operating requirements: provide identification nameplates and labels for control items in English.

1.5 SUBMITTALS

- .1 Submit for review single line electrical diagrams under plexiglass and locate at main service.
 - .1 Electrical distribution system in main electrical room.
- .2 Shop drawings:
 - .1 Submit wiring diagrams and installation details of equipment indicating proposed location, layout and arrangement, control panels, accessories, piping, ductwork, and other items that must be shown to ensure co-ordinated installation.
 - .2 Identify on wiring diagrams circuit terminals and indicate internal wiring for each item of equipment and interconnection between each item of equipment.
 - .3 Indicate of drawings clearances for operation, maintenance, and replacement of operating equipment devices.
 - .4 Submit and product data to Contract Administrator. Quantities as required.
 - .5 If changes are required, notify Contract Administrator of these changes before they are made.
- .3 Quality Control:
 - .1 Provide CSA certified equipment and material. Where CSA certified equipment and material is not available, submit such equipment and material to authority having jurisdiction for special approval before delivery to Site.
 - .2 Submit test results of installed electrical systems and instrumentation.
 - .3 Permits and fees: in accordance with General Conditions of contract.
 - .4 Submit, upon completion of Work, load balance report as described in PART 3 - LOAD BALANCE.
 - .5 Submit certificate of acceptance from authority having jurisdiction upon completion of Work to Contract Administrator.
- .4 Manufacturer's Field Reports: submit to Contract Administrator manufacturer's written report, within 3 days of review, verifying compliance of Work and electrical system and instrumentation testing, as described in PART 3 - FIELD QUALITY CONTROL.

1.6 QUALITY ASSURANCE

- .1 Qualifications: electrical Work to be carried out by qualified, licensed electricians or apprentices in accordance with authorities having jurisdiction as per the conditions of Provincial Acts respecting manpower vocational training and qualification.
 - .1 Employees registered in provincial apprentices program: permitted, under direct supervision of qualified licensed electrician, to perform specific tasks.
 - .2 Permitted activities: determined based on training level attained and demonstration of ability to perform specific duties.

1.7 SYSTEM STARTUP

- .1 Instruct Operating Personnel in operation, care and maintenance of systems, system equipment and components.
- .2 Arrange and pay for services of manufacturer's factory service Contract Administrator to supervise start-up of installation, check, adjust, balance and calibrate components and instruct operating personnel.
- .3 Provide these services for such period, and for as many visits as necessary to put equipment in operation, and ensure that operating personnel are conversant with aspects of its care and operation.

1.8 OPERATING INSTRUCTIONS

- .1 Provide for each system and principal item of equipment as specified in technical sections for use by operation and maintenance personnel.
- .2 Operating instructions to include following:
 - .1 Wiring diagrams, control diagrams, and control sequence for each principal system and item of equipment.
 - .2 Start up, proper adjustment, operating, lubrication, and shutdown procedures.
 - .3 Safety precautions.
 - .4 Procedures to be followed in event of equipment failure.
 - .5 Other items of instruction as recommended by manufacturer of each system or item of equipment.
- .3 Post instructions where directed.
- .4 For operating instructions exposed to weather, provide weather-resistant materials or weatherproof enclosures.
- .5 Ensure operating instructions will not fade when exposed to sunlight and are secured to prevent easy removal or peeling.

Part 2 Products

2.1 MATERIALS AND EQUIPMENT

- .1 Material and equipment to be CSA certified. Where CSA certified material and equipment is not available, obtain special approval from authority having jurisdiction before delivery to Site and submit such approval as described in PART 1 - SUBMITTALS.

2.2 ELECTRIC MOTORS, EQUIPMENT AND CONTROLS

- .1 Verify installation and co-ordination responsibilities related to motors, equipment and controls, as indicated.
- .2 Control wiring and conduit: in accordance with Section 26 29 03 - Control Devices except for conduit, wiring and connections below 50 V which are related to control systems specified in mechanical sections and as shown on mechanical drawings.

2.3 WARNING SIGNS

- .1 Warning Signs: in accordance with requirements of authority having jurisdiction and Contract Administrator.
- .2 Decal signs, minimum size 175 x 250 mm.

2.4 WIRING TERMINATIONS

- .1 Ensure lugs, terminals, screws used for termination of wiring are suitable for either copper or aluminium conductors.

2.5 EQUIPMENT IDENTIFICATION

- .1 Identify electrical equipment with nameplates and labels to as follows:
 - .1 Nameplates: lamicoid 3 mm matt white finish face, black core, lettering accurately aligned and engraved into core mechanically attached with self tapping screws.
 - .2 Sizes as follows:

NAMEPLATE SIZES

| | | | |
|--------|-------------|---------|--------------------|
| Size 1 | 10 x 50 mm | 1 line | 3 mm high letters |
| Size 2 | 12 x 70 mm | 1 line | 5 mm high letters |
| Size 3 | 12 x 70 mm | 2 lines | 3 mm high letters |
| Size 4 | 20 x 90 mm | 1 line | 8 mm high letters |
| Size 5 | 20 x 90 mm | 2 lines | 5 mm high letters |
| Size 6 | 25 x 100 mm | 1 line | 12 mm high letters |
| Size 7 | 25 x 100 mm | 2 lines | 6 mm high letters |

- .2 Labels: embossed plastic labels with 6mm high letters unless specified otherwise.
- .3 Wording on nameplates and labels to be approved by Contract Administrator prior to manufacture.
- .4 Allow for minimum of twenty-five (25) letters per nameplate and label.
- .5 Nameplates for terminal cabinets and junction boxes to indicate system and/or voltage characteristics.
- .6 Disconnects, starters and contactors: indicate equipment being controlled and voltage.
- .7 Terminal cabinets and pull boxes: indicate system and voltage.
- .8 Transformers: indicate capacity, primary and secondary voltages.

2.6 WIRING IDENTIFICATION

- .1 Identify wiring with permanent indelible identifying markings, numbered, on both ends of phase conductors of feeders and branch circuit wiring.
- .2 Maintain phase sequence and colour coding throughout.
- .3 Colour coding: to CSA C22.1.
- .4 Use colour coded wires in communication cables, matched throughout system.

2.7 CONDUIT AND CABLE IDENTIFICATION

- .1 Colour code conduits, boxes and metallic sheathed cables.
- .2 Code with plastic tape or paint at points where conduit or cable enters wall, ceiling, or floor, and at 5 m intervals.
- .3 Colours: 25 mm wide prime colour and 15 mm wide auxiliary colour.

| | <u>Prime</u> | <u>Auxiliary</u> |
|-----------------------------|--------------|------------------|
| up to 250 V | Yellow | |
| up to 600 V | Yellow | Green |
| up to 5 kV | Yellow | Blue |
| up to 15 kV | Yellow | Red |
| Telephone | Green | |
| Other Communication Systems | Green | Blue |
| Fire Alarm | Red | |
| Emergency Voice | Red | Blue |
| Other Security Systems | Red | Yellow |

2.8 FINISHES

- .1 Shop finish metal enclosure surfaces by application of rust resistant primer inside and outside, and at least two coats of finish enamel.
 - .1 Paint outdoor electrical equipment "equipment green" finish.
 - .2 Paint indoor switchgear and distribution enclosures light grey to EEMAC 2Y-1.

Part 3 Execution

3.1 INSTALLATION

- .1 Do complete installation in accordance with CSA C22.1 except where specified otherwise.
- .2 Do overhead and underground systems in accordance with CSA C22.3 No.1 except where specified otherwise.

3.2 NAMEPLATES AND LABELS

- .1 Ensure manufacturer's nameplates, CSA labels and identification nameplates are visible and legible after equipment is installed.

3.3 CONDUIT AND CABLE INSTALLATION

- .1 Install conduit and sleeves prior to pouring of concrete.
 - .1 Sleeves through concrete: schedule 40 plastic, sized for free passage of conduit, and protruding 50 mm.
- .2 If plastic sleeves are used in fire rated walls or floors, remove before conduit installation.
- .3 Install cables, conduits and fittings embedded or plastered over, close to building structure so furring can be kept to minimum.

3.4 LOCATION OF OUTLETS

- .1 Locate outlets in accordance with Section 26 05 32 - Outlet Boxes, Conduit Boxes and Fittings.
- .2 Do not install outlets back-to-back in wall; allow minimum 150 mm horizontal clearance between boxes.
- .3 Change location of outlets at no extra cost or credit, providing distance does not exceed 3000 mm, and information is given before installation.
- .4 Locate light switches on latch side of doors.

3.5 MOUNTING HEIGHTS

- .1 Mounting height of equipment is from finished floor to centreline of equipment unless specified or indicated otherwise.
- .2 If mounting height of equipment is not specified or indicated, verify before proceeding with installation. Install electrical equipment at following heights unless indicated otherwise.
 - .1 Local switches: 1200 mm.
 - .2 Wall receptacles:
 - .1 General: 300 mm.
 - .2 Above top of continuous baseboard heater: 200 mm.
 - .3 Above top of counters or counter splash backs: 100 mm.
 - .4 In mechanical rooms: 1400 mm.
 - .3 Panelboards: as required by Code or as indicated.

3.6 CO-ORDINATION OF PROTECTIVE DEVICES

- .1 Ensure circuit protective devices such as overcurrent trips, relays and fuses are installed to required values and settings.

3.7 FIELD QUALITY CONTROL

- .1 Load Balance:
 - .1 Measure phase current to panelboards with normal loads (lighting) operating at time of acceptance; adjust branch circuit connections as required to obtain best balance of current between phases and record changes.
 - .2 Measure phase voltages at loads and adjust transformer taps to within 2% of rated voltage of equipment.
 - .3 Provide upon completion of work, load balance report as directed in PART 1 - SUBMITTALS: phase and neutral currents on panelboards, dry-core transformers and motor control centres, operating under normal load, as well as hour and date on which each load was measured, and voltage at time of test.
- .2 Conduct following the tests;
 - .1 Power distribution system including phasing, voltage, grounding and load balancing.

- .2 Circuits originating from branch distribution panels.
- .3 Lighting and its control.
- .4 Motors, heaters and associated control equipment including sequenced operation of systems where applicable.
- .5 Insulation resistance testing:
 - .1 Megger circuits, feeders and equipment up to 350 V with a 500 V instrument.
 - .2 Megger 350-600 V circuits, feeders and equipment with a 1000 V instrument.
 - .3 Check resistance to ground before energizing.
- .3 Carry out tests in presence of Contract Administrator.
- .4 Provide instruments, meters, equipment and personnel required to conduct tests during and at conclusion of project.
- .5 Manufacturer's Field Services:
 - .1 Obtain written report from manufacturer verifying compliance of Work, in handling, installing, applying, protecting and cleaning of product and submit Manufacturer's Field Reports as described in PART 1 - SUBMITTALS.
 - .2 Provide manufacturer's field services consisting of product use recommendations and periodic Site visits for inspection of product installation in accordance with manufacturer's instructions.
 - .3 Schedule Site visits, to review Work, as directed in PART 1 - QUALITY ASSURANCE.

3.8 CLEANING

- .1 Clean and touch up surfaces of shop-painted equipment scratched or marred during shipment or installation, to match original paint.
- .2 Clean and prime exposed non-galvanized hangers, racks and fastenings to prevent rusting.

END OF SECTION